


L14P1 L14P2







DESCRIPTION

The L14P1/L14P2 are silicon phototransistors mounted in a narrow angle, TO-18 package.

FEATURES

- Hermetically sealed package
- Narrow reception angle
- Devices can be used as a photodiode by wiring the collector and base leads.



L14P1 L14P2

ABSOLUTE MAXIMUM RATINGS (T _A = 25°C unless otherwise specified)								
Parameter	Symbol	Rating	Unit					
Operating Temperature	T _{OPR}	-65 to +125	°C					
Storage Temperature	T _{STG}	-65 to +150	°C					
Soldering Temperature (Iron)(3,4,5 and 6)	T _{SOL-I}	240 for 5 sec	°C					
Soldering Temperature (Flow)(3,4 and 6)	T _{SOL-F}	260 for 10 sec	°C					
Collector to Emitter Breakdown Voltage	V _{CEO}	30	V					
Collector to Base Breakdown Voltage	V _{CBO}	40	V					
Emitter to Base Breakdwon Voltage	V _{EBO}	5	V					
Power Dissipation (T _A = 25°C) ⁽¹⁾	P _D	300	mW					
Power Dissipation (T _C = 25°C) ⁽²⁾	P _D	600	mW					

NOTE:


- 1. Derate power dissipation linearly 3.00 mW/°C above 25°C ambient.
- 2. Derate power dissipation linearly 6.00 mW/°C above 25°C case.
- 3. RMA flux is recommended.
- 4. Methanol or isopropyl alcohols are recommended as cleaning agents.
- 5. Soldering iron tip 1/16" (1.6mm) minimum from housing.
- 6. As long as leads are not under any stress or spring tension.
- 7. Light source is a GaAs LED emitting light at a peak wavelength of 940 nm.
- 8. Figure 1 and figure 2 use light source of tungsten lamp at 2870°K color temperature. A GaAs source of 3.0 mW/cm² is approximately equivalent to a tungsten source, at 2870°K, of 10 mW/cm².

ELECTRICAL / OPTICAL CHARACTERISTICS (TA =25°C) (All measurements made under pulse conditions)								
PARAMETER	TEST CONDITIONS	SYMBOL	MIN	TYP	MAX	UNITS		
Collector-Emitter Breakdown	$I_{C} = 10 \text{ mA}, Ee = 0$	BV _{CEO}	30		_	V		
Emitter-Base Breakdown	I _E = 100 μA, Ee = 0	BV _{EBO}	5.0		_	V		
Collector-Base Breakdown	I _C = 100 μA, Ee = 0	BV _{CBO}	40		_	V		
Collector-Emitter Leakage	V _{CE} = 12 V, Ee = 0	I _{CEO}	_		100	nA		
Reception Angle at 1/2 Sensitivity		θ		±8		Degrees		
On-State Collector Current L14P1	Ee = 0.5 mW/cm ² , $V_{CE} = 5 V^{(7,8)}$	I _{C(ON)}	6.5		_	mA		
On-State Collector Current L14P2	Ee = 0.5 mW/cm ² , $V_{CE} = 5 V^{(7,8)}$	I _{C(ON)}	13.0			mA		
On-State Photodiode Current	$Ee = 0.3 \text{ mW/cm}^2, V_{CB} = 5 \text{ V}$	I _{CB(ON)}		6.0		μΑ		
Rise Time	$I_{\rm C}$ = 10 mA, $V_{\rm CC}$ = 5 V, $R_{\rm L}$ =100 Ω	t _r		10		μs		
Fall Time	$I_{\rm C}$ = 10 mA, $V_{\rm CC}$ = 5 V, $R_{\rm L}$ =100 Ω	t _f		12		μs		
Saturation Voltage L14P1	$I_C = 0.8 \text{ mA}, Ee = 0.6 \text{ mW/cm}^{2(7,8)}$	V _{CE(SAT)}	_		0.40	V		
Saturation Voltage L14P2	$I_C = 1.6 \text{ mA}, Ee = 0.6 \text{ mW/cm}^{2(7,8)}$	V _{CE(SAT)}			0.40	V		



L14P1 L14P2

Figure 1. Light Current vs. Collector to Emitter Voltage



V_{CE}, COLLECTOR TO EMITTER VOLTAGE (V)








Figure 4. Light Current vs. Temperature











L14P1 L14P2

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body,or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.